

**WARNING:** DISCONNECT POWER AT THE MAIN FUSE BOX BEFORE INSTALLATION.

**WARNING:**

This fixture is intended for installation in accordance with the National Electrical Code (NEC) and all local code specifications. If you are not familiar with code requirements, installation by a certified electrician is recommended.

Before assembly, remove all parts and part packages from box. If anything is missing, please contact the retailer from which the product was purchased.




ITEM#: MLE1500-5-30


1. Carefully pull house wires out of junction box so they are easily accessible during installation.
2. Position mounting bracket (A) so tabs on mounting bracket are pointing down towards the floor.
3. Align slots in mounting bracket (A) with holes in junction box. Thread each junction box screw (B) into slots in mounting bracket (A) and into holes in junction box. Tighten junction box screws (B) to secure mounting bracket (A) to junction box.

**CAUTION:** Make sure house wires are pulled completely through hole in mounting bracket.

**DO NOT** pinch wires between mounting bracket and ceiling.



4. Strip 3/4" of insulation from ends of fixture wires.
5. Slightly loosen ground screw on mounting bracket (A). Do not completely remove ground screw. Wrap house ground wire (copper) around ground screw, leaving enough ground wire to attach to fixture ground wire. Twist end of fixture ground wire and end of house ground wire (copper) together. Twist wire connector (C) onto ends of wires. Completely tighten wire connector (C). Reference chart below for correct wire connections.



Connect Supply (House) Ground Copper Wire to:

Bare Copper Wire or,

Bare Silver Wire or,

Green Insulated Wire.

6. Twist end of house lead wire (black) and end of fixture lead wire together. Twist wire connector (C) onto ends of wires. Completely tighten wire connector (C). Twist end of house neutral wire (white) and end of fixture neutral wire together. Twist wire connector (C) onto ends of wires. Completely tighten wire connector (C). Reference chart to the right for correct wire connections.
7. Wrap electrical tape (not included) around wire connectors (C) and wires. Ensure wires are securely fastened into wire connectors.
8. Carefully push all wires and wire connectors into junction box.

| Connect Black Lead Supply (House) Wire to:                                                                                                   | Connect White Neutral Supply (House) Wire to:            |
|----------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------|
| Black Wire or,                                                                                                                               | White Wire or,                                           |
| *Parallel Cord (Round and Smooth) or,                                                                                                        | *Parallel Cord (Square and Ridged) or,                   |
| No printed words on wire insulation or,                                                                                                      | Printed words on wire insulation or,                     |
| Insulated Wire (other than green) with Copper Conductor.                                                                                     | Insulated Wire (other than green) with Silver Conductor. |
| *When parallel wire (SPT 1 & SPT 2) is used:<br>The lead wire is round in shape or smooth.<br>The neutral wire is square in shape or ridged. |                                                          |

